

EQUIVALENT TO	0123F	0141M	0127F	01FD3	01F31	01FD4	0149FD	0141F
Omron	G5V1	G2E	G5V2	G6S	G6H	G6K	G6DS	
Tyco	V23111						PCN	V23092/SNR
Nais	HY		DS2Y	TX	TQ	AGQ	PA	PE
DIMENSIONS	12,5x7,5x10,0	15,7x11,0x12,0	20,2x10,0x11,5	15,0x7,5x9x0	14,0x9,0x5,0	10,0x6,5x5,4	20,0x5,0x12,5	28,0x5,0x15,0
CONTACTS	1C	1C	2C	2C	2C	2C	1A	1A, 1C
CURRENT	1A	1A	2A	2A	1A	2A	5A	6A
VOLTAGES (V)	1,5 a 24	3 a 24	3 a 48	1,5 a 48	1,5 a 24	1,5 a 24	5 a 24	5 a 60
POWER (W)	0,15-0,2	0,2-0,36-0,45	0,15-0,58	0,1-0,14-0,2	0,1-0,14-0,2	0,1-0,14-0,2	0,12-0,18	0,17-0,21
DRAWING								
PHOTO								
EQUIVALENT TO	0132F	0133F	013FF/FD	01152F	0118FD	0111F	0105F	01FE7
Omron	G5SB/G5Q	G5LA	G5LE-VD	G6RN	G2RL	G8P	G6C	
Tyco	RE/REL	T7S						
Nais	JQ/PQ	JS	JSM					
DIMENSIONS	18,4x10,2x15,3	20,5x10,2x15,3	19,0x15,2x15,5	21,0x16,0x20,6	28,5x10,1x12,5	29,0x12,7x15,7	32,2x27,0x20,1	20,0x15,0x10,2
CONTACTS	1A, 1C	1A, 1C	1A, 1C	1A, 1C	1A,1B,1C,2A,2B,2C	1A,1B,1C,2A,2B,2C	1A,1B,1C	1A,1B,2A,2B,1A+1C
CURRENT	3A(1C)-10A(1A)	10A	10A	16A(1C)-20A(1A)	5A(2C)-10A(1C)	8A(2C)-16A(1C)	20A(1C)-30A(1A)	8A-10A
VOLTAGES (V)	3 a 48	3 a 48	5 a 48	3 a 48	5 a 60	5 a 110	12-277AC/5-110DC	3 a 24
POWER (W)	0,2-0,45	0,2-0,45	0,36	0,36	0,22-0,29 y 0,36	0,4	2,0VA-0,9W	0,2-0,28
DRAWING								
PHOTO								